

High- Q impurity photon states bounded by a photonic-band-pseudogap in an optically-thick photonic-crystal slab

Se-Heon Kim,^{1,2,*} Andrew Homyk,^{2,3} Sameer Walavalkar,^{2,3} and Axel Scherer^{1,2,3}

¹*Department of Physics, California Institute of Technology, Pasadena, CA 91125, USA*

²*Kavli Nanoscience Institute, California Institute of Technology, Pasadena, CA 91125, USA*

³*Department of Electrical Engineering, California Institute of Technology, Pasadena, CA 91125, USA*

(Dated: September 26, 2012)

We show that, taking a two-dimensional photonic-crystal slab system as an example, surprisingly high quality factors (Q) over 10^5 are achievable, even in the *absence* of a rigorous photonic-band-gap. We find that the density of in-plane Bloch modes can be controlled by creating additional photon feedback from a finite-size photonic-crystal boundary that serves as a *low- Q* resonator. This mechanism enables significant reduction in the coupling strength between the bound state and the extended Bloch modes by more than a factor of 40.

PACS numbers: 42.60.Da, 42.70.Qs, 42.50.Pq

Significant reduction in the radiation rate of a point-like emitter can be achieved by setting up mirrors around it,[1] or by employing photonic crystals (PhCs),[2, 3] which is a photonic analogue of atomic crystals for electron waves.[4] It has long been believed that the existence of the photonic-band-gap (PBG) is essential to achieving a *spatially localized* high- Q electromagnetic bound state using a PhC cavity. Thus, most efforts so far have focused on artificial dielectric structures possessing a PBG.[5–8] Donor- or acceptor-like impurity photon states can be formed at the location of a crystal defect.[9] Such a localized state (with small mode volume, V) has drawn much attention in the context of cavity quantum electrodynamics (cQED) experiments[10, 11] where the use of high Q/V cavities are essential to enhancing light-matter interaction.

Due to fabrication related difficulties, three-dimensional (3-D) PhCs have been replaced with a lower dimensional counterpart relying on index guiding in one or two dimensions. Often, this assumes the form of a thin dielectric slab[12], whose thickness (T) is roughly equal to half the effective wavelength ($T \approx \lambda/2n_{eff}$) in order to optimize the size of the in-plane PBG. One representative such a design is shown in Fig. 1(a) and (b). Note that a 2-D PhC with the triangular-lattice of air-holes supports the PBG only for *even* guided modes, where the symmetry is defined with respect to the mirror plane at $z = 0$. However, this *incomplete* PBG does not preclude the possibility of high- Q defect states, because the same mirror symmetry ensures that the defect mode with the *even* symmetry will be *completely* decoupled from all *odd* guided modes. Lowering the dimensionality often creates new symmetries that can be exploited, making the condition for localized photon states less stringent.

It is well established that an optically-*thick* PhC slab does not support any PBG for both *even* and *odd* symmetries[12, 13]. As an example, in Fig. 1(d), we present a photonic band structure (ω - k diagram) for *even*

Bloch modes in a *thick* PhC slab with $T = 1.731a$. The formation of the PBG is hindered by the higher-order slab modes lying between the 1st and the 5th bands. Note that the energy gap defined by the 1st and the 5th bands ($\Delta\omega_{1-5}$) will remain more or less constant as T increases and, in the limit of $T \rightarrow \infty$, $\Delta\omega_{1-5}$ will approach the PBG of an ideal 2-D PhC[12]. Also note that, though all bands, $\mathbf{E}_{(Bloch)}(\mathbf{r})$, shown in Fig. 1(d) are mutually orthogonal, the bound state in a defect region, $\mathbf{E}_{(cav)}(\mathbf{r})$, in general, *can* couple to any of the higher-order Bloch modes. However, this coupling strength, $|\kappa_{c,B}| \sim |\int d^3\mathbf{r} \Delta\epsilon \mathbf{E}_{(cav)} \cdot \mathbf{E}_{(Bloch)}^*|$ [14], shouldn't be strong, because $\mathbf{E}_{(cav)}(z)$ resembles $\mathbf{E}_{(Bloch)}(z)$ of the 1st band. In this sense, any optically-thick PhC slab bears a *pseudo*-PBG. Similar pseudo-energy gap in solid state physics can create *resonance* states[15]. Here, the photonic counterpart can be easily manipulated with high precision by means of the mature modern nanofabrication technology.

In this Letter, we will show how $\kappa_{c,B}$ can be controlled by setting up simple mirror boundaries around the finite size PhC resonator [Fig. 1(a)]. The additional boundary conditions imposed by the mirrors can alter the density of Bloch states in the momentum space ($\mathbf{k}$ -space). Thus, in relation to the $\mathbf{k}$ spectrum of $\mathbf{E}_{(cav)}$ [16], $\kappa_{c,B}$ can experience significant change. We note that the situation is analogous to the well-known cQED example of a point dipole source ($\approx$ the hexapole mode) in an optical resonator ($\approx$ the low- Q resonator defined by the boundary termination)[17].

We perform fully-vectorial 3-D numerical simulations using the finite-difference time-domain method (FDTD) to understand the mutual interaction between $\mathbf{E}_{(cav)}$ and $\mathbf{E}_{(Bloch)}$. First, we study the energy decay rate (γ) of the hexapole mode[18] shown in Fig. 1(b). The total decay rate (γ_{tot}) can be decomposed into the decay rates into the horizontal direction (γ_{horz}) and the out-of-plane direction (γ_{vert}). Then, γ is translated into Q factor through $Q \equiv \omega/\gamma$. Thus, $1/Q_{tot} = 1/Q_{horz} + 1/Q_{vert}$ [13].




FIG. 1: (a) A 3-D rendering of the photonic-crystal cavity to be studied in this Letter. The number of photonic-crystal hole layers (N layer) and the boundary termination (p) are to be varied. a is the lattice constant of the 2-D triangular-lattice photonic-crystal with the background air-holes, R , of $0.35a$. The refractive index of the slab is assumed to be 3.4. The six nearest neighbor holes are reduced ($Rm = 0.25a$) and slightly pushed away (by a scale factor of 1.1) from the defect center. (b) $|E|^2$ distribution of the hexapole mode in a $T = 1.731a$ slab. (c) Cross-sectional views of the first five lowest Bloch modes at M -point. These modes all have even symmetries with respect to the plane at $z = 0$. (d) The photonic band structure for all even Bloch modes. The hexapole mode resonance shown in (b) ($\omega_n \sim 0.265$) is represented by the horizontal line, in which ω_n is the normalized frequency defined by $\omega_n \equiv a/\lambda$.

Note that we set up detection planes for the Poynting energy flux ($\sim \mathbf{E} \times \mathbf{H}^*$) away from the mirror boundary, so that γ_{horz} accounts for the reflection/transmission at the PhC-air discontinuity.

In Fig. 2, we consider the two boundary terminations of $p = \infty$ and $p = 1.2a$. For $p = \infty$, Q_{tot} tends to be saturated by Q_{horz} ; Q_{tot} approaches $44,000 \sim 48,000$




FIG. 2: Q_{tot} , Q_{vert} , and Q_{horz} of the hexapole mode for two different boundary terminations, (a) $p = \infty$ and (b) $p = 1.2a$. When the mirror boundary effect is weak ($p = \infty$), Q_{horz} is limited by about 60,000 due to the coupling to the in-plane Bloch modes. However, in the case of the abrupt termination by air, Q_{horz} can be made over 2,600,000.

as N layer > 8 [13]. In fact, this particular choice of the boundary termination $p = \infty$ approximately ensures negligibly small reflection off the interface. Alternatively, we can simulate the transparent boundary condition by overlapping the perfectly matched layer in the FDTD with the PhC air-holes[19], which results in the similar saturated Q_{horz} of $\sim 60,000$ ($\equiv Q_{horz}^{(sat)}$).

Usually, the reflection coefficient at the PhC-air boundary is not so large as $0.5 \sim 0.6$ [20]. However, drastically different behaviors can be seen by forming simple mirrors with $p = 1.2a$ [Fig. 2(b)]. (i) All Q values *strongly* modulate with N layer. (ii) Q_{horz} can be brought up to a surprisingly high value of $\sim 2.6 \times 10^6$ at N layer = 10. This implies that γ_{horz} can be reduced by more than a factor of 40 compared with the case of minimal reflection ($p = \infty$). (iii) Since $Q_{horz} \gg Q_{vert}$, now the hexapole mode emits more photons into the out-of-plane direction. Interestingly, all Q s modulate in the same fashion; whenever Q_{horz} is peaked, so is Q_{vert} . Therefore, the abrupt boundary termination does not simply redirect the in-plane guided energy into the out-of-plane radiation. Rather, there should be a common physical principle for the observed enhancement and suppression. Moreover, note that the maximum Q_{tot} of 1.4×10^5 in the present case can be further increased by employing a higher Q_{vert} cavity mode. Also note that Q_{vert} of the hexapole mode is slightly lowered by the use of finite space grids ($\Delta = a/20$) used in the FDTD simulation[21].

More detailed analyses are performed as we finely tune




FIG. 3: (a-c) Top-down views ($|\mathbf{E}|^2$) of the hexapole resonances in a $T = 1.731a$ slab as we increase N layer from 4 to 9 (in the clockwise direction) for three different boundary terminations of $p = 0.8, 1.0$, and $1.2a$, respectively. (d) The hexapole resonances in a *thin* ($T = 0.488a$) slab for $p = \infty$ are presented in the same manner used in (a-c). Note that this thin slab possesses the in-plane photonic-band-gap. (e) Q_{horz} and (f) Q_{tot} for the hexapole resonances shown in (a-d).

the mirror boundary conditions. Specifically, we tune p in the range of $0.8 - 1.2a$ as a means to control the phase shift (ϕ) upon reflection. Here, we will provide direct *graphical* evidence for the enhancement/suppression of the in-plane Bloch modes. In order to visualize the very weak near-fields in the outskirt regions, we adopt the saturated color scheme in which $1/1000$ of the intensity maximum is taken as the upper bound. In Fig. 3(a)-(c), we present $|\mathbf{E}_{(cav)}(\mathbf{r}_{||}, z = 0)|^2$ of the hexapole mode for three different $p = 0.8, 1.0$, and $1.2a$. We take only one-sixth area (cut by the two Γ - K lines) of the hexapole mode profile for each N layer, then combined with plots of different N layers to create a one image filling upto 360° . We also provide a similar plot for a PBG-confined hexapole mode in Fig. 3(d), corresponding to a slab thickness of $0.488a$. For quantitative analyses, we also provide graphs for Q_{tot} [Fig. 3(f)] and Q_{horz} [Fig. 3(g)] as well as the resonance frequency shift $\Delta\omega_n/\omega_n$ [Fig. 3(e)].

We find that, at $(N \text{ layer}, p) = (9, 0.8a)$, $|\mathbf{E}_{(Bloch)}(\mathbf{r}_{||})|^2$ is *almost completely suppressed*, which is comparable with that of the PBG-confined case shown in Fig. 3(d). On the other hand, at certain combinations of $(N \text{ layer}, p)$, $|\mathbf{E}_{(Bloch)}(\mathbf{r}_{||})|^2$ becomes quite strongly pronounced; for example, see $(7, 0.8a)$, $(8, 1.0a)$, and $(7, 1.2a)$. For small N layer such as at $(N \text{ layer} \leq 5, p = 1.0a)$, it seems natural to have more intense photon tunneling than the equivalent PBG-confined case. How-

ever, by *slightly* tuning p , the strong in-plane loss in the previous case can be greatly reduced by more than a factor of 10, whose resultant Q_{tot} and Q_{horz} can be higher than those of the PBG-confined case[22]. This result may find a practical importance in applications where a device miniaturization is required while keeping Q reasonably high.

We find that $|\mathbf{E}_{(Bloch)}(\mathbf{r}_{||})|^2$ variations can explain peaks and dips observed in Q_{horz} or Q_{tot} . We also note that the more intensified $|\mathbf{E}_{(Bloch)}(\mathbf{r}_{||})|^2$ in the outskirt region can contribute to the excessive scattering losses into the vertical direction, thereby lowering Q_{vert} . In short, what we have shown here is that $\kappa_{c,B}$ strongly depends on the detailed boundary conditions. $\kappa_{c,B}$ obviously depends on the size of the hexagonal boundary, which determines the phase thickness of the 2-D cavity. It is also understandable that p is a very critical parameter controlling the density of in-plane Bloch modes, as has been seen in many cQED examples of an atom and a cavity. Further evidence of this analogy can be found in Fig. 3(e), which reports the fractional frequency shift. Even using sufficiently thick PhC mirrors with $N \text{ layer} \geq 6$, the thick-slab cases show noticeable modulations in $\Delta\omega_n/\omega_n$ order of $\pm 10^{-5}$, while the PBG-confined case does not. These energy-level shifts[17] are signatures of the coupling between $\mathbf{E}_{(cav)}(\mathbf{r})$ and $\mathbf{E}_{(Bloch)}(\mathbf{r})$ and can be explained in terms of $\kappa_{c,B}$ [14].




FIG. 4: (a) In our coupled-mode model, the hexapole mode is assumed to couple only to the Γ - M wavevectors. For further simplification, the solution for the entire system is *projected* into the x direction. The hexapole symmetry ensures the odd mirror symmetry with respect to the $x = 0$ plane. (b) Q_{horz} enhancement factors in Eq. 4. All plots assume $r_M = 0.6$.

Though the FDTD provides very accurate first-principle means to understand the $\kappa_{c,B}$ modulation, we have not been quite convinced as to how the simple boundary termination (hence the *low-Q*) can enable such large modulations in Q_{horz} (and Q_{tot} as well). Therefore, it would be instructive to develop a simple model in the spirit of the coupled mode theory (CMT)[14, 23]. To begin, we would like to note that the in-plane hexapole mode profile, $|\mathbf{E}_{cav}(\mathbf{r}_{||})|^2$, can be approximated in terms of the three M -point wavevectors of $\mathbf{k}_{M1} = (0, 1)|\mathbf{k}_M|$, $\mathbf{k}_{M2} = (\sqrt{3}/2, 1/2)|\mathbf{k}_M|$, and $\mathbf{k}_{M3} = (\sqrt{3}/2, -1/2)|\mathbf{k}_M|$ with $|\mathbf{k}_M| = 2\pi/\sqrt{3}a$. For example, $|\mathbf{E}_{cav}(\mathbf{r}_{||})|^2 \approx |\sin(\alpha\mathbf{k}_{M1} \cdot \mathbf{r}_{||}) - \sin(\alpha\mathbf{k}_{M2} \cdot \mathbf{r}_{||}) - \sin(\alpha\mathbf{k}_{M3} \cdot \mathbf{r}_{||})|^2$ with a correction factor $\alpha > 1$ [24]. For our hexapole mode, α is ~ 1.1 based on the $\mathbf{k}$ -space intensity distribution, $|\tilde{\mathbf{E}}_{cav}(\mathbf{k})|^2$ [21]. This is the reason the outskirts region of the hexapole mode resembles the M -point Bloch modes[25].

To simplify our CMT model, we assume that the hexapole mode couples *only* to the six M -point wavevectors, $\beta \times (\mathbf{k}_{M1}, \mathbf{k}_{M2}, \mathbf{k}_{M3}, -\mathbf{k}_{M1}, -\mathbf{k}_{M2}, -\mathbf{k}_{M3})$, where β is a scale factor ~ 0.7 as evidenced from the photonic band structure in Fig. 1(d). Now we emphasize that these M -point wavevectors ($\{\beta\mathbf{k}_M\}$) are *closed* upon reflections at the six hexagonal facets. Thus, we may consider the whole set of wavevectors, $\{\beta\mathbf{k}_M\}$, as a *channel* or a *port* in the CMT formulation [Fig. 4(a)]. Under these assumptions, our hexapole mode can be viewed as *side-coupled* to the port[26]. Then, the time evolution of the hexapole mode's energy amplitude (b) can be described by

$$\frac{db}{dt} = \left[i\omega_0 - \frac{\gamma_{vert} + \gamma_{horz}}{2} \right] b + \kappa_M S_{+M}, \quad (1)$$

where the last term describes the *total incoming* power as a result of the feedback by the boundary termination. We assume that S_{+M} is measured at the *inner* boundary

of the partial mirror shown in Fig. 4(a) and consists of the Bloch waves with $\{\beta\mathbf{k}_M\}$. The CMT states that κ_M cannot be arbitrarily determined but rather it should be connected by the decay rate into the waveguide port such that $\kappa_M = \sqrt{2\gamma_{horz}}e^{-i\theta_M}$.

When the effect of the photon feedback is weak as in the case of $p = \infty$, we can set $S_{+M} = 0$ in Eq. 1. Then, $|b|^2$ decays exponentially with $\gamma_{horz} = |\kappa_M|^2/2 = \omega_0/Q_{horz}^{(sat)}$. However, when there is a feedback mechanism, γ_{horz} is not a constant but varies with θ_M and ϕ_M (reflection phase). For this general situation, we need additional set of equations, which can be derived from the CMT[27]. For example, the outgoing power (S_{-M}) and the incoming power (S_{+M}) are related each other by b through

$$S_{-M} = e^{-2i\theta_M} S_{+M} + \sqrt{2\gamma_{horz}}e^{-i\theta_M} b. \quad (2)$$

We define the scattering matrix of the partial mirror such that $S_{+M} = r_M e^{i\phi_M} S_{-M}$. Then, the modified Q_{horz} ($\equiv Q_{horz}^{feed}$) can be written using the definition of Q ($\equiv \omega \times$ [total energy stored in the resonator]/[total power loss into the port]),

$$Q_{horz}^{feed} = \omega^{feed} \frac{|b|^2}{t_M^2 |S_{-M}|^2} \quad (3)$$

In general, ω^{feed} (the resonance frequency in the presence of the feedback) differs from the original ω_0 as we have seen from the FDTD result in Fig. 3(e). However, we can assume $\omega^{feed} \approx \omega_0$ since the fractional change in ω is much less than 1%. Note that the partial mirror is assumed to be lossless such that $r_M^2 + t_M^2 = 1$.

After solving S_{-M} and S_{+M} for b , we obtain the expression for the Q_{horz} enhancement, $Q_{horz}^{feed}/Q_{horz}^{(sat)}$ ($= \gamma_{horz}/\gamma_{horz}^{feed}$),

$$\frac{Q_{horz}^{feed}}{Q_{horz}^{(sat)}} = \frac{1 + r_M^4 - 2r_M^2 \cos(2\phi_M + 4\theta_M)}{(1 - r_M^2)(1 + r_M^2 + 2r_M \cos(\phi_M - 2\theta_M))}. \quad (4)$$

Fig. 4(b) shows plots of Eq. 4 for several ϕ_M values, while r_M is fixed at 0.6. The model also expects drastic modulations in Q_{horz} depending where we locate the resonator with respect to the $|\mathbf{E}|^2$ envelop of the low- Q Fabry-Perot type resonator. For example, when $\phi_M = 1.0\pi$, Q_{horz} enhancement is maximized to be about 5 at $\theta_M = \pi$ (=effective half wavelength), which can be understood considering that $|\mathbf{E}|^2 = 0$ at $x = 0$. Interestingly, tuning ϕ_M slightly can greatly improve the enhancement; $\phi_M = 0.75\pi$ results in the maximum $Q_{horz}^{feed}/Q_{horz}^{(sat)}$ very close to 30. We also find that the ϕ_M tuning inevitably alters the optimal θ_M for Q , which agrees with the FDTD results in Fig. 3; the small tuning in p changes the optimal N layer for Q .

It should be noted that we have assumed only one $\mathbf{k}$ -port and such a large enhancement holds true only for that port. However, if the defect state could excite many in-plane Bloch waves with different wavevectors thereby creating many $\mathbf{k}$ -ports, the overall Q_{horz} enhancement contributed from different $\mathbf{k}$ -ports will be averaged out to be 1 as Eq. 4 expects. For example, multiple $\mathbf{k}$ ports might be involved if T were too thick (since this would allow more higher-order slab modes with many $\mathbf{k}$ s) or if the boundary termination would not retain the hexapole symmetry (since $\mathbf{k}_M$ cannot be conserved upon reflections).

In summary, we study a quasi-bound photon state within a PhC that does not possess a rigorous PBG. We show that the density of in-plane Bloch modes can be controlled by the termination of the finite-size PhC. The coupling strength between the bound state and the extended Bloch modes can be reduced by more than a factor of 40 in the case of a thick PhC slab. The air-suspended slab structure assumed in this study may appear impractical. However, low index cladding material can be placed underneath as a supporting structure or a metal cladding to the sides of the hexagonal boundary can be used as a clamp[28], which could also be used as an electrode for current injection. By removing the thickness constraint of $T \approx \lambda/2n_{eff}$, many unconventional cavity designs which were previously discarded because they cannot support a PBG can now be reconsidered, such as the use of a *thick*-slab for the design of current-injection nanolasers[29].

This work was supported by the Defense Advanced Research Projects Agency under the Nanoscale Architecture for Coherent Hyperoptical Sources program (W911NF-07-1-0277) and by the National Science Foundation under NSF CIAN ERC (EEC-0812072). A. Homyk appreciates the generous support of the ARCS Foundation.

* Electronic address: seheon@caltech.edu

- [1] E. M. Purcell, Phys. Rev. **69**, 681 (1946).
- [2] E. Yablonovitch, Phys. Rev. Lett. **58**, 2059 (1987).
- [3] S. John, Phys. Rev. Lett. **58**, 2486 (1987).
- [4] J. D. Joannopoulos, S. G. Johnson, J. N. Winn, and R. D. Meade, *Photonic Crystals: Molding the Flow of Light* (Princeton University Press, Princeton, NJ, 2008), 2nd ed.
- [5] E. Yablonovitch, J. Opt. Soc. Am. B **10**, 283 (1993).
- [6] S. Noda, K. Tomoda, N. Yamamoto, and A. Chutinan, Science **289**, 604 (2000).
- [7] E. Chow, S. Lin, S. Johnson, P. Villeneuve, J. Joannopoulos, J. Wendt, G. Vawter, W. Zubrzycki, H. Hou, and A. Alleman, Nature **407**, 983 (2000).
- [8] M. Maldovan and E. L. Thomas, Nat. Mater. **3**, 593 (2004).
- [9] E. Yablonovitch, T. J. Gmitter, R. D. Meade, A. M. Rappe, K. D. Brommer, and J. D. Joannopoulos, Physical Review Letters **67**, 3380 (1991).
- [10] T. Yoshie, A. Scherer, J. Hendrickson, G. Khitrova, H. M. Gibbs, G. Rupper, C. Ell, O. B. Shchekin, and D. G. Deppe, Nature **432**, 200 (2004).
- [11] S. Noda, M. Fujita, and T. Asano, Nature **1**, 449 (2007).
- [12] S. G. Johnson, S. Fan, P. R. Villeneuve, J. D. Joannopoulos, and L. A. Kolodziejski, Physical Review B **60**, 5751 (1999).
- [13] S.-H. Kim, J. Huang, and A. Scherer, Opt. Lett. **37**, 488 (2012).
- [14] H. A. Haus, *Waves and Fields in Optoelectronics* (Prentice-Hall, Englewood Cliffs, N. J., 1984).
- [15] O. Madelung, *Introduction to Solid-State Theory* (Springer-Verlag, Berlin, 1978), chap. 14.
- [16] K. Srinivasan and O. Painter, Opt. Express **10**, 670 (2002).
- [17] E. A. Hinds, in *Cavity Quantum Electrodynamics* (Academic Press, Inc, Orlando, 1994), edited by P. R. Berman.
- [18] H.-Y. Ryu, M. Notomi, and Y.-H. Lee, Appl. Phys. Lett. **83**, 4294 (2003).
- [19] M. Koshiba, Y. Tsuji, and S. Sasaki, Microwave and Wireless Components Letters, IEEE **11**, 152 (2001).
- [20] E. Istrate, A. A. Green, and E. H. Sargent, Phys. Rev. B **71**, 195122 (2005).
- [21] S.-H. Kim, S.-K. Kim, and Y.-H. Lee, Phys. Rev. B **73**, 235117 (pages 13) (2006).
- [22] For the thin PhC slab, we find that $p \sim 1.0a$ causes excessive scattering losses at the termination boundaries, resulting in the lower Q than $p = \infty$ case. For fair comparisons between *thin*- and *thick* slabs, we assume both modes oscillate at approximately same resonant wavelengths of 1300 nm, which can be achieved by choosing a of the thin-slab and the thick-slab to be 410 nm and 350 nm, respectively.
- [23] S. Fan, W. Suh, and J. D. Joannopoulos, J. Opt. Soc. Am. A **20**, 569 (2003).
- [24] O. Painter and K. Srinivasan, Phys. Rev. B **68**, 035110 (2003).
- [25] G.-H. Kim, Y.-H. Lee, A. Shinya, and M. Notomi, Opt. Express **12**, 6624 (2004).
- [26] The side-coupling configuration may describe the situation better than the butt-coupling, because 1) the point-like defect structure occupies only a small fraction of the entire 2-D cavity and 2) the 2-D Bloch waves rather *freely* move from the left side to the right side without being assisted by the resonance of the defect.
- [27] C. Manolatou, M. J. Khan, S. Fan, P. R. Villeneuve, H. A. Haus, and J. D. Joannopoulos, IEEE Journal of Quantum Electronics **35**, 1322 (1999).
- [28] J. Huang, S.-H. Kim, and A. Scherer, Opt. Express **18**, 19581 (2010).
- [29] S.-H. Kim, J. Huang, and A. Scherer, J. Opt. Soc. Am. B **29**, 577 (2012).